



Standard Electronic Ballast Program Start Series Biax lamp operation

TWO LAMP OPERATION		
Lamp Type	FT40T5	FT39T5
Rated Lamp Watts	40	40
Ballast Factor	1.00	1.00
Input Power (W)	75	75
Input Current (A) @120V	0.53	0.53
Input Current (A) @277V	0.23	0.23
Power Factor	>.99	>.99
THD	<10%	<10%
Ballast Efficacy Factor	1.33	1.33

ONE LAMP OPERATION		
Lamp Type	FT40T5	FT39T5
Rated Lamp Watts	40	40
Ballast Factor	1.00	1.00
Input Power (W)	42	42
Input Current (A) @120V	0.35	0.35
Input Current (A) @277V	0.15	0.15
Power Factor	98%	98%
THD	<10%	<10%
Ballast Efficacy Factor	2.50	2.50

BALLAST SPECIFICATIONS


- Ballast shall have a five-year warranty.
- Ballast shall be UL certified
- Ballast shall be sound rated Class A.
- Ballast shall have a Lamp Current Crest Factor of <1.7.
- Ballast shall withstand line transients as specified in ANSI C62.41-1991
- Ballast shall comply with the limits of FCC Part 18C for Non-Consumer equipment.
- Ballast shall have a lamp operating frequency greater than 20kHz.
- Ballast shall have a 0°F minimum lamp starting temperature.
- Ballast shall be potted.
- Ballast shall be Program Start
- Ballast shall be Series Lamp Operation
- Ballast shall have end of lamp life shutdown protection
- Ballast shall have minimum Power Factor of 98% for primary lamp operation
- Ballast shall operate within +/- 10% of the ballast specified line voltage at 60 Hz.
- Ballast shall have a maximum case hot spot temperature of 90 Celsius.

AMERICAN BALLAST 47800 FREMONT BLVD, FREMONT, CA 94538
1-888-313-8188 Fax: (510) 445-1678 Email: info@americanballast.com

AB2-40-PS-UNV-BX

WIRING DIAGRAMS


TWO LAMP OPERATION



ONE LAMP OPERATION



BALLAST DIMENSIONS



AMERICAN BALLAST 47800 FREMONT BLVD, FREMONT, CA 94538
1-888-313-8188 Fax: (510) 445-1678 Email: info@americanballast.com